

PM-HOS4-DA-U 4K Dante Audio w/ HDMI Output Card for PM Switchers



The **PM-HOS4-DA-U** is a Dante Audio with HDMI ports output board for PureMedia™ matrix switchers supporting UltraHD/4K resolutions and Dante/AES67 IP audio. Each **PM-HOS4-DA-U** has primary and secondary RJ-45 ports for IP audio and four HDMI ports.

Key Features

- Dante or AES67 selectable via software
- Primary and secondary IP Audio ports
- Selectable IP audio latency
- Four HDMI ports
- Supports up to 3840 x 2160 @ 30Hz resolutions

Technical Specifications

CONNECTOR TYPES	(4) Female HDMI Type A outputs (2) RJ-45 ports (primary and secondary IP audio connections)
OPERATION STANDARD	DVI 1.0, HDMI 1.4
HDCP COMPATIBLE	HDCP 2.2
MAXIMUM PIXEL CLOCK	300MHz
MAXIMUM RESOLUTION	Up to 3840 x 2160 @ 30Hz
EQUALIZATION	Auto
HDMI DIGITAL AUDIO FORMATS	LPCM up to 7.1, Dolby Digital 5.1, Dolby Digital Plus, Dolby TrueHD, DTS-HD, DTS-HD Master Audio
IP AUDIO TRANSMITTER TYPE	Dante/AES67, Software Selectable
IP OUTPUT CHANNEL	HDMI Audio 32 channel
IP AUDIO FORMAT	Uncompressed, 24bit, 48KHz
IP AUDIO LATENCY	Selectable, 0.25ms, 0.5ms, 1.0ms, 2.0ms, 5.0ms
SINGLE BOARD WEIGHT	1 lb. (0.45 kg)